



**AeroAudio**

WWW.AEROAUDIO.EU




**MPX**


MPX2LCD - MPX3LCD

**DETECTOR**



# SPECIFICATIONS


 HTML5 webinterface


 2/3 MPX inputs


 1 MPX output


 SNMP

 Mail server

 Attack time, release time, threshold,  
left/right, detector (audio level, 19kHz)

 Tally control

 LCD display

 Jack 6,3mm headphone output

## MPX 2

The detector is designed to monitor 2 MPX signals and switch to the output. The input that is active, so connected to the output, is also displayed on the display and the audio signal is audible on the headset.

If the “main” input (MPX input 1) is lost, MPX input 2 will be switched to the output. This is visible on the display of the detector by the text BACKUP: MPX2. This text also blinks so it is clear that the main input has failed.

Switching the mpx signal (from one of the inputs to the output) is done by a relay so that the signal is not affected.

The detector also checks the 19Khz signal. Its status can be seen in the web interface. The detector has a network interface for displaying status, configuring configuration and sending alerts. Status notifications occur by means of Emails. The settings for this can be done in the web interface. This interface can be operated via a web browser (Firefox, Google Chrome, etc.).

At the back you can find the connections for the MPX inputs and the network connection.

There is also a 9 pin D connector with the text “Tally”

A relay contact is connected to this, which indicates the status of the detector. Pin 1 = NC Pin 2 = NO Pin 6 = common

## MPX 3

The detector is designed to monitor up to 3 MPX signals and switch one of them to the output. The input that is active, i.e. the input that is switched to the output, is also shown at the display, and its audio signal can be listened to at the headphone jack.

On an outage of the main input, one of the other two sources will be switched to the output. The display of the device will indicate this with the text BACKUP: MPX1, MPX 2 or MPX3. This status is also shown in the HTML interface.

The MPX signals are switched through relays, so that there is zero influence on the signal.

On a detected silence, the priority of inputs that is switched to, is on the order of the lowest input number. For example, if inputs 2 and 3 are both present, then input 2 will always be connected to the output. With inputs 1 and 2, it is always input 1.

The status reports of this are done by means of emails and SNMP. All the settings can be made in the 4 HTML pages. These can be configured with a web browser (Firefox, Google chrome, etc.)

The detector also checks the 19 kHz signal. This is also shown in the HTML interface. You can choose whether the detection takes place by audio silence or the absence of the 19 kHz signal.

Preferable, use input 1 as the Main input. The reason is that on a power outage, the relays switches input 1 to the output.